


SAHYADRI®

ISO 9001:2015 Certified

SAHYADRI ELECTRO CONTROLS (I) PVT. LTD.

SECO



TAP POSITION INDICATOR – BCD INPUT

(TYPE: SRV 115B)

10, VINAY COMPLEX, 1ST CROSS, RAJGOPAL NAGAR MAIN ROAD, GANAPATHI NAGAR,
PEENYA III PHASE, BANGALORE – INDIA - 560058

Mail: mkt@secoindia.co.in & sales@secoindia.co.in, Web: www.secoindia.co.in

SAHYADRI (SECO) make **TAP POSITION INDICATOR with BCD INPUT (SRV 115B)** is a controller based design to indicate the power transformer tap position through seven segment LED display which depends on the BCD Encoder.

The unit is connected to power transformer Onload tap changer contacts (BCD Encoder) to the respective terminals B1(LSB), B2, B3, B4, B5 & B6 (MSB) along with common terminal as marked on the rear side of the unit. The unit shows the respective taps of the transformer depending on the contacts in Binary code format.

FEATURES:-

- Microcontroller based design for high accuracy
- Visual – 2 Digit - Seven segment display
- With TEST facility
- Panel mounting type with aesthetic value
- Robust & rugged i.e. suitable for industrial environment
- Accuracy & consistent reliability
- Suitable up to 39 Taps
- Polycarbonate front cover for protection

TECHNICAL SPECIFICATIONS:-

- **Aux. Supply voltage:** 110 or 230V AC +/- 15%, 50Hz
- **Power consumption:** < 60W
- **Input:** Potential free NO contacts
- **TAP display:** Binary code with 6 inputs
- **Display:** 7 Segment LED display
- **Panel cutout size:** 92 x 92 mm
- **Front Facia:** 48 x 96 mm
- **Depth:** 110 mm
- **Box:** ABS plastic

BACK VIEW



SAHYADRI®

ISO 9001:2015 Certified



No 10, Vinay Complex, 1st Cross, Rajgopal nagar Main Road,
Ganapati Nagar, Peenya 3rd Phase,
Bangalore-560058

080-4149 2637 / +91 9035048537 / +91 9448408537 / +91 9980544028

After Sales / Service : +91 9606040824

mkt@secoindia.co.in / sales@secoindia.co.in / manjunatha@secoindia.co.in