

**SAHYADRI ELECTRO CONTROLS (I) PVT. LTD.**


**SECO**



## **DIGITAL COUNTER - 4 CHANNEL (TYPE : SC 130)**

# 10, VINAY COMPLEX, 1<sup>ST</sup> CROSS, RAJGOPAL NAGAR MAIN ROAD, GANAPATHI NAGAR,  
PEENYA III PHASE, BANGALORE – INDIA - 560058

Mail: [mkt@secoindia.co.in](mailto:mkt@secoindia.co.in) & [sales@secoindia.co.in](mailto:sales@secoindia.co.in), Web: [www.secoindia.co.in](http://www.secoindia.co.in)




**SAHYADRI (SECO)** make **Four Channel Counter** is an unique device designed with advance technology Microcontroller. This product is user friendly with universal application like complex counting. The SC 130 series Four channel is widely accepted in packing, Pharmaceutical, textile Industries and also used in Substation SCADA communication.



## FEATURES:-

- Microcontroller based design
- Seven segment Display
- 4 Digit counter with 4 channels
- With SMPS power supply – Wide range
- Four channel display with separate Reset built-in Push button
- Modular type


## TECHNICAL SPECIFICATIONS:-

- **Aux. supply:** 18 to 110V DC or 75 to 275V DC
  - **Input:** Potential free contacts, Proximity switches, Limit switches
  - **Range:** 9999 counts
  - **Display:** 4 digit high bright 7 segment display
  - **Accuracy:** 100% - No missing pulses
  - **Reset:** Front inbuilt Push Buttons for each channel
  - **Remote Reset:** Terminal provided for external push buttons
  - **Sensing time:** Less than 10m Seconds
  - **Memory:** Inbuilt memory to store the previous pulses for power failure
  - **Box:** 96 x 96 Sq. mm
  - **Panel cutout:** 92 x 92 mm
  - **Depth:** 120 mm
- 


## WIRING DIAGRAM



4- CHANNEL COUNTER	
TER. NO	DESCRIPTION
1	COMMON - RESET (CR)
2	RESET - A (RA)
3	RESET - B (RB)
4	RESET - C (RC)
5	RESET - D (RD)
10 & 11	AUX. SUPPLY 18 - 100 VDC
14	COMMON-COUNTER (C)
15	COUNTER- A (CA)
16	COUNTER- B (CB)
17	COUNTER- C (CC)
18	COUNTER- D (CD)
SL. NO.	



PANEL CUTOUT - 92X92 mm  
BEZZEL - 96X96 mm



TYPICAL WIRING DIAGRAM

ALL DIMENSIONS ARE IN MM.

DRAWN BY	HSV	REV. NO.	0	ISSUED ON	15.12.19		DRAWING TITLE: APPLICATION DIAGRAM OF 4 CHANNEL DIGITAL COUNTER	DRG NO. SECO/AD/SC130	SH.NO	01	SECO
APPD. BY	BSM			DRAWN ON	15.12.19				CONTD.	-	

**SIDE VIEW**



**BACK VIEW**



**SAHYADRI®**

ISO 9001:2015 Certified



No 10, Vinay Complex, 1st Cross, Rajgopal nagar Main Road,  
Ganapati Nagar, Peenya 3rd Phase,  
Bangalore-560058

080-4149 2637 / +91 9035048537 / +91 9448408537 / +91 9980544028

After Sales / Service : +91 9606040824

mkt@secoindia.co.in / sales@secoindia.co.in / manjunatha@secoindia.co.in